


## R1150H シリーズ マーキング仕様

### ● SOT-89-5



- ① : D (固定)
  - ②, ③ : 設定電圧
  - ④ : タイプ (A、B、C、D)
  - ⑤, ⑥ : ロットナンバー
- (型式ナンバーと略号の対応表を参照して下さい。)

### ● 型式ナンバーと略号の対応表

#### R1150HxxxA シリーズ

型式ナンバー	略号				設定電圧	
	①	②	③	④	VR	VD
R1150H002A	D	0	2	A	3.3V	2.5V
R1150H003A	D	0	3	A	5.0V	4.3V
R1150H006A	D	0	6	A	5.0V	4.5V
R1150H010A	D	1	0	A	3.0V	4.2V
R1150H011A	D	1	1	A	7.0V	2.8V
R1150H012A	D	1	2	A	12.0V	4.7V
R1150H013A	D	1	3	A	7.5V	4.3V
R1150H014A	D	1	4	A	7.5V	4.7V
R1150H015A	D	1	5	A	3.0V	2.5V
R1150H019A	D	1	9	A	14.0V	15.0V
R1150H021A	D	2	1	A	3.6V	4.3V
R1150H023A	D	2	3	A	12.0V	4.2V
R1150H027A	D	2	7	A	3.6V	9.0V
R1150H029A	D	2	9	A	3.6V	7.8V
R1150H033A	D	3	3	A	3.1V	4.5V
R1150H039A	D	3	9	A	3.3V	6.8V
R1150H040A	D	4	0	A	3.3V	5.0V
R1150H042A	D	4	2	A	5.6V	4.5V
R1150H043A	D	4	3	A	9.0V	9.9V
R1150H044A	D	4	4	A	8.0V	8.9V
R1150H045A	D	4	5	A	5.0V	5.6V
R1150H046A	D	4	6	A	5.6V	3.0V
R1150H047A	D	4	7	A	12.0V	5.0V
R1150H048A	D	4	8	A	5.0V	7.5V
R1150H049A	D	4	9	A	2.85V	4.5V
R1150H050A	D	5	0	A	5.4V	3.0V

#### R1150HxxxB シリーズ

型式ナンバー	略号				設定電圧	
	①	②	③	④	VR	VD
R1150H002B	D	0	2	B	3.3V	2.5V
R1150H003B	D	0	3	B	5.0V	4.3V
R1150H004B	D	0	4	B	2.5V	2.3V
R1150H005B	D	0	5	B	3.3V	2.9V
R1150H006B	D	0	6	B	5.0V	4.5V
R1150H021B	D	2	1	B	3.6V	4.3V
R1150H024B	D	2	4	B	3.3V	3.6V
R1150H025B	D	2	5	B	4.0V	5.0V
R1150H035B	D	3	5	B	3.3V	3.8V
R1150H036B	D	3	6	B	3.3V	5.6V
R1150H037B	D	3	7	B	2.5V	4.1V
R1150H038B	D	3	8	B	5.0V	2.3V

#### R1150HxxxD シリーズ

型式ナンバー	略号				設定電圧	
	①	②	③	④	VR	VD
R1150H002D	D	0	2	D	3.3V	2.5V
R1150H016D	D	1	6	D	5.0V	3.5V
R1150H017D	D	1	7	D	3.3V	2.9V
R1150H018D	D	1	8	D	5.0V	3.0V
R1150H020D	D	2	0	D	5.0V	4.2V
R1150H022D	D	2	2	D	3.3V	2.8V
R1150H026D	D	2	6	D	3.3V	2.3V
R1150H028D	D	2	8	D	5.0V	2.1V
R1150H030D	D	3	0	D	3.3V	2.2V
R1150H031D	D	3	1	D	3.3V	2.0V
R1150H032D	D	3	2	D	3.4V	2.0V

#### R1150HxxxC シリーズ

型式ナンバー	略号				設定電圧	
	①	②	③	④	VR	VD
R1150H007C	D	0	7	C	3.5V	3.1V
R1150H008C	D	0	8	C	3.3V	4.2V
R1150H009C	D	0	9	C	5.0V	4.1V
R1150H020C	D	2	0	C	5.0V	4.2V
R1150H034C	D	3	4	C	5.0V	13.0V
R1150H041C	D	4	1	C	7.0V	7.5V